


# Product specification

## Switch mode power supply SNT9012-3



- ☐ Input range: 320 - 550 V<sub>AC</sub> or 450 - 780V<sub>DC</sub>
- ☐ Output range: 10.5 - 15.0 V<sub>DC</sub>
- ☐ **Boostfunction** 120% max. 30s
- ☐ no loss of performance in 2-phase operation
- ☐ simply mounting on DIN-rail or wall mounting with screws
- ☐ Device protection, shutdown on overtemperature
- ☐ Operating status shown by LED
- ☐ Parallel operation possible, polarity reversal protection, short circuit proof, overload and open circuit protected
- ☐ Vibration proof, suitable for the tropics - epoxy resin casted
- ☐ Output separated according to VDE0551
- ☐ Conforms to EMC and low voltage directive
- ☐ Safety according to VDE, EN, UL, CSA

### Application



The switch-mode power supplies of the SNT90-3 series are powerful and robust devices to power sensitive loads in a hard industrial environment. These features result from the modern construction with a good radio shielding and high reliability integrated in a functional and stable casing. The short circuit proof output DC voltage of this model can be adjusted from 10.5 - 15.0 V. This power supply is optimally suited for loads requiring high starting currents.


### Functional principle

In the power supply SNT9012-3 a flyback converter operates to transform the energy in two steps. During the conducting phase the diode is blocking, the inductor is energized and a magnetic field establishes. There is no electrical transmission; the consumer load is supplied with energy from the capacitor. When the switching transistor opens, the blocking phase begins. The current in the inductor cannot change immediately, discharges through the diode and a negative voltage establishes at the inductor. Now operating like a power source the inductor reloads the capacitor and supplies the consumer with energy. The energy flows from the inductor into the capacitor and the consumer and through the conducting diode back to the inductor.

### Design

Completely embedded with resin in an aluminium housing for mounting on a rail or mounting on wall with screws.



 Please read the data sheets and the operating instructions for further information